

PIXIE Smart RGBTW LED Strip Controller

#LT8915RTWBTAM



► Basic operation

- 1 click operate LED on/off
- To dim, long press and hold.
- 2 clicks go to maximum output
- 3 click change colour in white-red-green-blue-white order
- 4 clicks manual pairing
- 9 clicks reset device

Using 'control-button' on device and momentary inputs

► Applications

Residential dwellings for retrofit, renovation and new build; apartments; hotels and hospitality venues.

► What's in the box

1 x RGBTW LED Strip Controller, installation instructions

► Accessories

Bell Press mechs from 3rd party for optional connection to bell-press inputs.

**SCAN ME**

Download the PIXIE and
PIXIE PLUS Apps

**#LT8915RTWBTAM**

UNIVERSAL LED Strip Controller

The PIXIE Smart Universal LED strip controller is suitable 12v and 24V dimming and colour changing control of most manufacturers LED strip in the following combinations: RGBTW, RGBW, RGB, TW, Single Colour. It is a universal LED strip dimming with PIXIE smarts, bluetooth mesh and PIXIE app control built in.

Features

- Works with all types of LED strip - RGBTW, RGBW, RGB, TW, WW from all manufacturers
- Suitable for 12v and 24v LED strip dimming and colour changing
- Memory function activated by dip switch to toggle and memorise the status if a power outage occurs
- 2 x separate, optional connection of 3rd-party bell-press/ momentary inputs for simple wall control operation and integration possibilities.
- Compatible with all PIXIE Multifunction controllers
- Connect a power repeater to allow extension to the power capacity (extra power supply required) for very long LED runs.

Electrical

Input	12 - 24V
Min/ Max loads*	RGB Terminals: 6Amp Max Load
	CW/ WW: 7.5Amp Max Load
Operating ambient min/max (°C)	-10 to 45°
Typical wireless range	15 metres typical indoors **
IP Rating	IP20



PIXIE Smart RGBTW LED Strip Controller

#LT8915RTWBTAM

Related products

PIXIE Multifunction
#SMFBTAS



PIXIE Smart Dimmer
SDD300BTAM



PIXIE 600W Switch
#SWL600BTAM



Wiring Diagram



Power supply pictured to be purchased separately as needed to match the connected LED strip load and length.

Dimensions

PIXIE fits in

PIXIE fits in to a huge range of Australian wall plates



SCAN ME

SCAN ME



Download the PIXIE and
PIXIE PLUS Apps



PDF Prepared August 2023

© Copyright SAL - All Rights Reserved

Complete installation manual available at SAL National website.

